

Alarm Status

Centrix provides a dedicated page to view the current status of all alarms within your access group. This is available as follows;

- Open the main menu
- Expand the **Alarms** menu
- Select **Alarm Status**

Home / Alarm Status

Q Search

Enter search text...

Search By

Name Site

Show

Show inactive

Labels

None Selected

Severity

Information

Warning

Average

High

Critical

Select Multiple

Last Raise Time

	TRACK FLICK TDE TR 📍 Gatwick Fast	ACTIVATED: 5 DAYS AGO
	TRACK FLICK TDF TR 📍 Gatwick Fast	ACTIVATED: 6 DAYS AGO
	TRACK FLICK TDG TR 📍 Gatwick Fast	ACTIVATED: 6 DAYS AGO
	TRACK FLICK TDO TR 📍 Gatwick Fast	ACTIVATED: 6 DAYS AGO
	TRACK FLICK TGC-1 TR 📍 Gatwick Fast	ACTIVATED: 7 DAYS AGO
	TRACK FLICK TDC-1 TR 📍 Gatwick Fast	ACTIVATED: 7 DAYS AGO

By default, the view will show all **active** alarms for sites you have access to. You can also view the **inactive** alarms by selecting the **Show inactive** option in the **Search** box.

The **Search** box provides options to filter the alarm list by; name/site name, active only, labels and severity.

The listing can be sorted by **Last Raise Time** (default), **Alarm name** or **Site name**.

Clearing active alarms

You can clear a single alarm by clicking on the alarm in the listing and clicking **Clear Alarm**.

To clear multiple alarms;

- Click **Select Multiple** above the alarm listing
- Click on each alarm you want to clear, they should show check marks as you select them
- Click **Clear 3 Alarms** at the bottom of the page

You can click **Cancel Select** if you don't want to clear any alarms after clicking **Select Multiple**.

Alarm status details

To view more details of an alarm, click on it in the listing;

TRACK FLICK

TDE TR

📍 Gatwick Fast

ACTIVATED: 5 DAYS AGO

SEVERITY: **WARNING**

SUBSCRIBED: ☑

LAST RAISE: 31/MAY/2017 03:43:44.554 +0100

LAST UNSUPPRESSED RAISE: 31/MAY/2017 03:43:44.554 +0100

LAST ACTIVATING RAISE: 31/MAY/2017 03:08:35.971 +0100

✓ Clear Alarm


🔔 Alarm Raises

The coloured bar on the left is used to identify the **severity** of the alarm. This is also shown in text in the details.

Alarm raise history

To view a history of **alarm raises**, click the **Alarm Raises** button.

Home / Alarms / TDE TR / Raises

Show Suppressed Last Raise Time 

Track Flick Detected TRACK CIRCUIT (TDE TR) TRANSITIONED FROM UNOCCUPIED TO OCCUPIED WITHIN 1.672 SECONDS. THE MINIMUM EXPECTED TRACK OCCUPATION ON THIS CIRCUIT IS 2.000 SECONDS.	RAISE TIME: 31/MAY/2017 03:43:44.554 +0100 EVENT TIME: 31/MAY/2017 03:43:42.179 +0100 SUPPRESSED: ✘
Track Flick Detected TRACK CIRCUIT (TDE TR) TRANSITIONED FROM UNOCCUPIED TO OCCUPIED WITHIN 1.671 SECONDS. THE MINIMUM EXPECTED TRACK OCCUPATION ON THIS CIRCUIT IS 2.000 SECONDS.	RAISE TIME: 31/MAY/2017 03:24:05.059 +0100 EVENT TIME: 31/MAY/2017 03:24:04.900 +0100 SUPPRESSED: ✘
Track Flick Detected TRACK CIRCUIT (TDE TR) TRANSITIONED FROM UNOCCUPIED TO OCCUPIED WITHIN 0.823 SECONDS. THE MINIMUM EXPECTED TRACK OCCUPATION ON THIS CIRCUIT IS 2.000 SECONDS.	RAISE TIME: 31/MAY/2017 03:09:31.896 +0100 EVENT TIME: 31/MAY/2017 03:09:28.790 +0100 SUPPRESSED: ✘
Track Flick Detected TRACK CIRCUIT (TDE TR) TRANSITIONED FROM UNOCCUPIED TO OCCUPIED WITHIN 0.824 SECONDS. THE MINIMUM EXPECTED TRACK OCCUPATION ON THIS CIRCUIT IS 2.000 SECONDS.	RAISE TIME: 31/MAY/2017 03:08:35.971 +0100 EVENT TIME: 31/MAY/2017 03:08:33.876 +0100 SUPPRESSED: ✘

You can open the **Playback** panel for the site and date/time of an alarm raise by selecting the item in the listing, and pressing **View in playback**.